

Auflistung von Mikrofonbelegungen verschiedener Hersteller

Mikrofonbelegungen für CB-Funkgeräte (Fest- und Mobilstationen)

Zeichenerklärung:

MIC	Mikrofon/Modulation
GND	Masse
RX	Empfang/Audio
TX	Senden/PTT
MUTE	Squelch
EMG	Notrufkanal
UP-DOWN	Kanalwahl
DC	Versorgungsspannung/Strom
F-T	Funktionstasten
SCAN	Sendersuchlauf
MTM / MSP	Klinkenstecker 2,5 mm oder 3,5 mm

Alle Angaben ohne Gewähr!

Hersteller	Modell	Pin 1	Pin 2	Pin 3	Pin 4	Pin 5	Pin 6	Pin 7	Pin 8
ALAN	ALAN 100D	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	ALAN 100E	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 18	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 21E	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 28D	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 48D	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 48PLUS	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 48EXCEL	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 54	MIC	GND	RX	TX				
ALAN	MIDLAND 58E	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 77PLUS	MIC	RX	TX	UP-DOWN	GND	DC		
ALAN	MIDLAND 78PLUS	MIC	RX	TX	UP-DOWN	GND	DC		

ALBRECHT	AE 4002	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4012	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4100	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4180	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4200	MIC	GND	RX	TX				
ALBRECHT	AE 4300	MIC	GND	RX	TX				
ALBRECHT	AE 4400	MIC	GND	RX	TX				
ALBRECHT	AE 4500	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4550	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4600	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4650	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4700	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4800	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 4800 FM	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 5000	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 5080	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 5100	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 5150	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 5180	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 5280	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 8000	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	AE 8090	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	ALPHA 40B FM	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	ALPHA 40 FM	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	ALPHA 4000 FM	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	P 1000	GND	MIC	RX	TX				
ALBRECHT	PHANTOM 4012	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	PHANTOM 4012B	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	SKYLINE SM 2010	MIC	RX	TX	UP-DOWN	GND	DC		
ALBRECHT	SKYLINE 4000	MIC	RX	TX	UP-DOWN	GND	DC		

ASTRACOM	MA4012	MIC	GND	RX	TX				
ASTRACOM	MA40FM	MIC	GND	RX	TX				

DANITA	1540	GND	TX	MIC					
DANITA	MARK3	MIC	GND	TX	DC	RX			
DANITA	MARK5	MIC	GND	TX	GND	TX			

DNT	B 2740 AM/FM	MIC	GND	TX	GND	TX			
DNT	B 40 AM/FM	MIC	GND	TX	GND	TX			
DNT	CARAT	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	COCKPIT (II)	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	CONTACT 40 FM	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	CONTACT II/TRAFFIC 1	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	CONTACT III	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	COUPÉ	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	CV 2000	GND	NC	TX	MIC	NC			
DNT	FORMEL 1	GND	NC	TX	MIC	NC			
DNT	HIGHWAY	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	KURIER 5040	MIC	RX	TX	UP-DOWN	GND	DC		
DNT	KX 4012 COLONIA	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	M 2740 AM/FM	MIC	GND	TX	GND	TX	9V		
DNT	M 40 AM/FM	MIC	GND	TX	GND	TX	9V		
DNT	METEOR 8012	MIC	SCAN	TX	12V	UP-DOWN	GND		
DNT	METEOR SELEKTIV	MIC	SCAN	TX	12V	UP-DOWN	GND		
DNT	RALLEY	GND	NC	TX	MIC	NC			
DNT	SAPHIR	MIC	SCAN	TX	12V	UP-DOWN	GND		
DNT	SAPHIR 8012	MIC	SCAN	TX	12V	UP-DOWN	GND		
DNT	SCANNER	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	SCANNER FM	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	STRATO I	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	STRATO PLUS	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	TRANSIT	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	TRUCK STAR	MIC	RX	TX	GND	MUTE	6V	UP-DOWN	
DNT	ZIRKON	MIC	SCAN	TX	12V	UP-DOWN	GND		

GRUNDIG	CBH-CBM 100-3000	GND	TX	MIC					
---------	------------------	-----	----	-----	--	--	--	--	--

KAISER	KA 9018 FM/40	GND	TX	MIC	TX	GND			
KAISER	KA 9040 FM	GND	MIC	TX	RX				
KAISER	KE 901 5/40 BASIS	GND	MIC	TX	RX				
KAISER (NFT)	KA 4000 FM	GND	TX	MIC	TX	GND			
KAISER (NFT)	KA 901 2	MIC	GND	RX	TX				
KAISER (NFT)	KA 901 4	MIC	GND	RX	TX				
KAISER (NFT)	KA 9050	GND	MIC	TX	RX				

MAXON	MX 1000	MIC	RX	TX	UP-DOWN	GND	DC		
MAXON	MX 2000	MIC	RX	TX	UP-DOWN	GND	DC		
MAXON	MX 3000	MIC	RX	TX	UP-DOWN	GND	DC		
MAXON	MX 40-12 MERCURY	GND	MIC	TX	RX				

PAN	MEGA-TOP AM/FM	MIC	GND	RX	TX				
PAN	MEGA-TOP FM	MIC	GND	RX	TX				
PAN	MINI-TOP AM//FM	MIC	GND	RX	TX				
PAN	MINI-TOP FM	MIC	GND	RX	TX				
PAN	MINI-TOP LCD 8012	MIC	RX	TX	UP-DOWN	GND	DC		
PAN	MIRAGE	MIC	RX	TX	UP-DOWN	GND			
PAN	P 2000 BASIS	MIC	GND	RX	TX				
PAN	PC 40	GND	MIC	RX	TX				
PAN	PC 4012	MIC	RX	TX	UP-DOWN	GND	DC		
PAN	PC 50	MIC	GND	RX	TX				
PAN	PC 505	MIC	GND	RX	TX				
PAN	PC 80	MIC	RX	TX	UP-DOWN	GND	DC		
PAN	PCM 8112	MIC	RX	TX	UP-DOWN	GND	DC		
PAN	SCAN 4000 BASIS	MIC	GND	RX	TX				

PRESIDENT	GEORGE	MIC	RX	TX	UP-DOWN	GND	DC		
PRESIDENT	HARRY	MIC	TX	GND	NC	RX			
PRESIDENT	HERBERT	GND	MIC	TX	RX				
PRESIDENT	JACKSON	MIC	RX	TX	UP-DOWN	GND	DC		
PRESIDENT	JAMES	MIC	RX	TX	UP-DOWN	GND	DC		
PRESIDENT	JFK	MIC	RX	TX	UP-DOWN	GND	DC		
PRESIDENT	JOHNSON	MIC	RX	TX	UP-DOWN	GND	DC		
PRESIDENT	LINCOLN	MIC	RX	TX	UP-DOWN	GND	DC		
PRESIDENT	PC 40	GND	MIC	TX	RX				
PRESIDENT	TAYLOR	MIC	RX	TX	UP-DOWN	GND	DC		
PRESIDENT	VALERY	MIC	RX	TX	UP-DOWN	GND	DC		
PRESIDENT	WILSON	MIC	RX	TX	UP-DOWN	GND	DC		

STABO	MAGNUM M	MIC	GND	RX	TX				
STABO	XF 2540 BASIS	MIC	GND	RX	TX				
STABO	XF 4012N BASIS	MIC	GND	RX	TX				

STABO	XF 4012 BASIS	MIC	GND	RX	TX				
STABO	XF 5012 BASIS	MIC	GND	RX	TX				
STABO	XF 4000 BASIS	MIC	GND	RX	TX				
STABO	XF 9082 BASIS	MIC	RX	TX	F-T	GND			
STABO	XM 2240	MIC	GND	RX	TX				
STABO	XM 3200	MIC	GND	RX	TX				
STABO	XM 3400	MIC	GND	RX	TX				
STABO	XM 3500	MIC	GND	RX	TX				
STABO	XM 4000	MIC	GND	RX	TX				
STABO	XM 4012	MIC	GND	RX	TX				
STABO	XM 4012N	MIC	GND	RX	TX				
STABO	XM 4042	MIC	GND	RX	TX				
STABO	XM 5000	MIC	GND	RX	TX				
STABO	XM 5012	MIC	GND	RX	TX				
STABO	XM 6012	MUTE	UP-DOWN	DC	GND	MIC	TX	AUDIO	EMG
STABO	XM 7042	MIC	RX	TX	F-T	GND			
STABO	XM 7082	MIC	RX	TX	F-T	GND			
STABO	XRC TWINSTAR	MUTE	UP-DOWN	DC	GND	MIC	TX	AUDIO	EMG

TEAM	NEU UND 80CH	MIC	RX	TX	UP-DOWN	GND	DC		
TEAM	CLASSIC 4012	MIC	GND	RX	TX				
TEAM	COMPACT 4012	MIC	GND	RX	TX				
TEAM	EURO 3004F BASIS	MIC	GND	RX	TX				
TEAM	EURO 3100 BASIS	MIC	GND	RX	TX				
TEAM	EURO 3102 BASIS	MIC	GND	RX	TX				
TEAM	EURO 4012 BASIS	MIC	GND	RX	TX	UP-DOWN			
TEAM	EURO 404	MIC	GND	RX	TX				
TEAM	EURO 8012 BASIS	MIC	RX	TX	UP-DOWN	GND	DC		
TEAM	EURO B-3104AF BASIS	MIC	GND	RX	TX				
TEAM	JOSESTAR I	MIC	GND	RX	TX				
TEAM	LUCKY STAR 40	MIC	TX	UP-DOWN	GND	RX			
TEAM	MAGIC 4012	MIC	GND	RX	TX				
TEAM	MEMORY 5002	MIC	GND	RX	TX				
TEAM	SUPERSTAR 4012	MIC	GND	RX	TX				
TEAM	TSM 404	MIC	GND	RX	TX				
TEAM	TC 404	MIC	GND	TX	GND	TX			
TEAM	TC 404 B BASIS	MIC	GND	TX	GND	TX			
TEAM	TM 404	MIC	GND	TX	GND	TX			
TEAM	TRANSCOM	MIC	RX	TX	UP-DOWN	GND	DC		
TEAM	TRICOM 444	MIC	RX	TX	UP-DOWN	GND	DC		
TEAM	TRS 404	MIC	GND	RX	TX				
TEAM	TRX 4012	MIC	GND	RX	TX				
TEAM	TRX 404	MIC	GND	RX	TX				
TEAM	TS 1000	MIC	TX	UP-DOWN	GND	RX			
TEAM	TS 404	MIC	GND	TX	GND	TX			
TEAM	TS 404 FM	MIC	GND	RX	TX				
TEAM	TS M 4012	MIC	GND	RX	TX				

UNIDEN	P 1000	GND	MIC	TX	RX				
UNIDEN	PC 404	GND	MIC	TX	RX				
UNIDEN	PRO 420e	GND	MIC	TX	RX				
UNIDEN	PRO 440e	GND	MIC	TX	RX				
UNIDEN	PRO 450e	GND	MIC	TX	RX				
UNIDEN	PRO 460	GND	MIC	TX	RX				

WIPE	5070	MIC	GND	RX	TX				
WIPE	5080	MIC	GND	RX	TX				
WIPE	5090	MIC	GND	RX	TX				
WIPE	B 5070 BASIS	MIC	GND	RX	TX				
WIPE	B 5080 BASIS	MIC	GND	RX	TX				
WIPE	B 5090 BASIS	MIC	GND	RX	TX				

ZODIAC	B 4040 BASIS	MIC	GND	TX	DC	RX			
ZODIAC	M 144	MIC	GND	TX	DC	RX			
ZODIAC	M 244	MIC	GND	TX	DC	RX			
ZODIAC	M 4040	MIC	GND	TX	DC	RX			
ZODIAC	M 8000	MIC	GND	TX	DC	RX			
ZODIAC	P 2040 ©	MIC	GND	TX	DC	RX			

Mikrofonbelegungen für CB-Funkgeräte (Handfunkgeräte)

Zeichenerklärung:

SPEAKER	Lautsprecher (Audio)
MIC	Mikrofon/Modulation
PTT	Senden/TX
2,5 v.K	Klinkenstecker 2,5 mm vorderer Kontakt
2,5 m.K	Klinkenstecker 2,5 mm mittlerer Kontakt
2,5 h.K	Klinkenstecker 2,5 mm hinterer Kontakt
3,5 v.K	Klinkenstecker 3,5 mm vorderer Kontakt
3,5 h.K	Klinkenstecker 3,5 mm hinterer Kontakt

Alle Angaben ohne Gewähr!

Hersteller	Modell	2,5 v.K	2,5 m.K	2,5 h.K	3,5 v.K	3,5 h.K
ALAN	ALAN 39	MIC(NF)	PTT	MASSE	SPEAKER	MASSE
ALAN	ALAN 42 PLUS	MIC(NF)PTT		MASSE	SPEAKER	MASSE
ALAN	ALAN 95	SPEAKER		MASSE	MIC(NF)PTT	MASSE
ALAN	ALAN 95 PLUS	MIC(NF)PTT		MASSE	SPEAKER	MASSE
ALAN	ALAN 98D	MIC(NF)PTT		MASSE	SPEAKER	MASSE
ALAN	ALAN 98E	MIC(NF)PTT		MASSE	SPEAKER	MASSE
ALAN	ALAN 80	MIC(NF)PTT		MASSE	SPEAKER	MASSE

ALBRECHT	AE 2200	2,5 MTM / 3,5 MSP
----------	---------	-------------------

DANITA	608	2,5 / 3,5 mm
--------	-----	--------------

KAISER (NFT)	CBX 40	2,5 / 3,5 mm
--------------	--------	--------------

TEAM	EXPERT 98	2,5 MTM / 3,5 MSP
TEAM	MINI COM	2,5 MTM / 3,5 MSP
TEAM	KP 4000	2,5 MTM / 3,5 MSP